

阅读申明

- 1.本站收集的数据手册和产品资料都来自互联网，版权归原作者所有。如读者和版权方有任何异议请及时告之，我们将妥善解决。
- 2.本站提供的中文数据手册是英文数据手册的中文翻译，其目的是协助用户阅读，该译文无法自动跟随原稿更新，同时也可能存在翻译上的不当。建议读者以英文原稿为参考以便获得更精准的信息。
- 3.本站提供的产品资料，来自厂商的技术支持或者使用者的心得体会等，其内容可能存在描述上的差异，建议读者做出适当判断。
- 4.如需与我们联系，请发邮件到marketing@iczoom.com，主题请标有“数据手册”字样。

Read Statement

1. The datasheets and other product information on the site are all from network reference or other public materials, and the copyright belongs to the original author and original published source. If readers and copyright owners have any objections, please contact us and we will deal with it in a timely manner.
2. The Chinese datasheets provided on the website is a Chinese translation of the English datasheets. Its purpose is for reader's learning exchange only and do not involve commercial purposes. The translation cannot be automatically updated with the original manuscript, and there may also be improper translations. Readers are advised to use the English manuscript as a reference for more accurate information.
3. All product information provided on the website refer to solutions from manufacturers' technical support or users the contents may have differences in description, and readers are advised to take the original article as the standard.
4. If you have any questions, please contact us at marketing@iczoom.com and mark the subject with "Datasheets" .

Board Level Products

HI2220P601R-10 (Part number example in **BOLD**)

HI	2220	P	601	R	-10
Product Series Code	Part Size Code	Rated Continuous Current Code	Impedance (Z) or Inductance (L) Value Code	Packaging Code	Additional Description
HI = High Current Chip Beads (≥3,000 mA)	0402	A ≤ 100 mA	First two numbers are Significant Digits. The last number indicates how many zeros are added to the significant digits for impedance.	B = Bulk Standard Thru-Hole Packaging	00 = Legacy Part Contains Lead
MI = Mid Current Chip Beads (≥1,000 mA to <3,000 mA)	0603	B = 200 mA	Impedance Examples	R = Tape & Reel Standard SMT Package	-10 = Lead Free Standard Catalog Part
LI = Low Current Chip Beads (<1,000 mA, <400 W Z)	0805	C = 300 mA			
HZ = High Impedance Chip Beads (<1,000 mA, ≥400 W Z)	1206	D = 400 mA	Inductance Examples		-11 to -99 = Non Standard or Custom Part
HF = High Frequency Chip Beads	1210	E = 500 mA			
LF = Low Frequency Chip Beads	1612	F = 600 mA	100 = 10 OHMS		
HR = High Bias Retention Chip Beads (>3,000 mA)	1806	G = 700 mA	101 = 100 OHMS		
CC = CAN-Bus Common Mode	1812	H = 800 mA	102 = 1,000 OHMS		
CM = Common Mode	1922	I = 900 mA	202 = 2,000 OHMS		
DI = Power Inductor	2021	J = 1,000 mA	060 = 6 OHMS		
DA = Multiline Array Chip	2220	K = 1,500 mA	600 = 60 OHMS		
IC = Chip Inductor	2520	L = 2,000 mA	601 = 600 OHMS		
	2545	M = 2,500 mA			
	2722	N = 3,000 mA			
	3032	O = 3,500 mA			
	3312	P = 4,000 mA			
	3322	Q = 4,500 mA			
	3421	R = 5,000 mA			
	3822	S = 5,500 mA			
	4545	T = 6,000 mA	470 = 47 nH		
	4732	U = 7,000 mA	471 = 470 nH		
	5022	V = 8,000 mA	472 = 4,700 nH		
	5441	W = 9,000 mA	473 = 47,000 nH		
	6032	X = 10,000 mA	474 = 470,000 nH		
		Y = 15,000 mA	475 = 4,700,000 nH		
		Z ≥ 20,000 mA			

29F0818-1SR-10 (Part number example in **BOLD**)

29	F	0818	-1	S	R	-10
Material Type	Product Type Code	Part Size Code	Minor Dimension Code	Board Mounting Style	Packaging Code	Additional Part Description
28 & 29 = Broad Band Material	C = Choke	Unique Part Identifier or Significant Dimension	Height or Length Variation	S = Surface Mount T = Thru-Hole	O = Bulk Standard R = Tape & Reel Standard SMT Package	-10 = Lead Free Standard Catalog Part
35 = Low Frequency Material	L = Axial Ledged Bead					
	F = Assembled Part					
	J = Radial Ledged Bead					-11 to -99 = Non Standard or Custom Part

Ferrite Cable Core Products

28B0250-100 (Part number example in **BOLD**)

28	B	0250	-1	0	0
Material Type	Product Type Code	Part Size Code	Selected Dimension Code	Additional Part Description	Additional Part Description
28 = Broad Band Material HF = High Frequency Material LF = Low Frequency Material	A = Split round cores (Snap-Ons) B = Round Cylindrical Cores R = Ribbon Cable Cores S = Split Ribbon Cores	28 material is usually measured in inches for OD. HF & LF Material OD & ID is usually measured in mm.	Usually Length	0 = Standard Part "A" Product Type Code A = Plastic Case B = Plastic Case "S" Product Type Code 0 = No Clip M = Metal Clip P = Plastic Clip A = Hinged Plastic Case	0 = Standard Part "A" Product Type Code 0 = White Case 2 = Black Case

FERRITE MATERIAL COMPARISON

LF, 28, HF Material Impedance vs Frequency (300 KHz - 2 GHz)
Impedance Materials for Cable & Wiring Harness Cores

