

阅读申明

- 1.本站收集的数据手册和产品资料都来自互联网，版权归原作者所有。如读者和版权方有任何异议请及时告之，我们将妥善解决。
- 2.本站提供的中文数据手册是英文数据手册的中文翻译，其目的是协助用户阅读，该译文无法自动跟随原稿更新，同时也可能存在翻译上的不当。建议读者以英文原稿为参考以便获得更精准的信息。
- 3.本站提供的产品资料，来自厂商的技术支持或者使用者的心得体会等，其内容可能存在描述上的差异，建议读者做出适当判断。
- 4.如需与我们联系，请发邮件到marketing@iczoom.com，主题请标有“数据手册”字样。

Read Statement

1. The datasheets and other product information on the site are all from network reference or other public materials, and the copyright belongs to the original author and original published source. If readers and copyright owners have any objections, please contact us and we will deal with it in a timely manner.
2. The Chinese datasheets provided on the website is a Chinese translation of the English datasheets. Its purpose is for reader's learning exchange only and do not involve commercial purposes. The translation cannot be automatically updated with the original manuscript, and there may also be improper translations. Readers are advised to use the English manuscript as a reference for more accurate information.
3. All product information provided on the website refer to solutions from manufacturers' technical support or users the contents may have differences in description, and readers are advised to take the original article as the standard.
4. If you have any questions, please contact us at marketing@iczoom.com and mark the subject with "Datasheets" .


SOT23 NPN SILICON PLANAR SWITCHING TRANSISTORS

ISSUE 2 – SEPTEMBER 94

FMMT3903
FMMT3904

COMPLIMENTARY TYPES – FMMT3903 - FMMT3905
FMMT3904 - FMMT3906

PARTMARKING DETAIL – FMMT3903 - 1W
FMMT3904 - 1A



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	V_{CBO}	60	V
CollectorEmitter Voltage	V_{CEO}	40	V
EmitterBase Voltage	V_{EBO}	6	V
Continuous Collector Current	I_C	200	mA
Power Dissipation at $T_{amb}=25^{\circ}C$	P_{tot}	330	mW
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150	$^{\circ}C$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ unless otherwise stated).

PARAMETER	SYMBOL	FMMT3903		FMMT3904		UNIT	CONDITIONS.
		MIN.	MAX.	MIN.	MAX.		
Collector Base Breakdown Voltage	$V_{(BR)CBO}$	60		60		V	$I_C=10\mu A, I_E=0$
CollectorEmitter Breakdown Voltage	$V_{(BR)CEO}$	40		40		V	$I_C=1mA, I_B=0^*$
EmitterBase Breakdown Voltage	$V_{(BR)EBO}$	6		6		V	$I_E=10\mu A, I_C=0$
CollectorEmitter CutOff Current	I_{CEX}		50		50	nA	$V_{CE}=30V, V_{BE(off)}=3V$
Base CutOff Current	I_{BEX}		50		50	nA	$V_{CE}=30V, V_{EB(off)}=3V$
Static Forward Current Transfer Ratio	h_{FE}	20 35 50 30 15	150	40 70 100 60 30	300		$I_C=0.1mA, V_{CE}=1V^*$ $I_C=1mA, V_{CE}=1V^*$ $I_C=10mA, V_{CE}=1V^*$ $I_C=50mA, V_{CE}=1V^*$ $I_C=100mA, V_{CE}=1V^*$
CollectorEmitter Saturation Voltage	$V_{CE(sat)}$		0.2 0.3		0.2 0.3	V	$I_C=10mA, I_B=1mA^*$ $I_C=50mA, I_B=5mA^*$
BaseEmitter Saturation Voltage	$V_{BE(sat)}$	0.65	0.85 0.95	0.65	0.85 0.95	V	$I_C=10mA, I_B=1mA^*$ $I_C=50mA, I_B=5mA^*$
Transition Frequency	f_T	250		300		MHz	$I_C=10mA, V_{CE}=20V$ $f=100MHz$
Output Capacitance	C_{obo}		4		4	pF	$V_{CB}=5V, I_E=0, f=100KHz$
Input Capacitance	C_{ibo}		8		8	pF	$V_{BE}=0.5V, I_C=0, f=100KHz$



FMMT3903 FMMT3904

SWITCHING CHARACTERISTICS (at $T_{amb} = 25^{\circ}\text{C}$ unless otherwise stated).

PARAMETER	SYMBOL	FMMT3903		FMMT3904		UNIT	CONDITIONS.
		MIN.	MAX.	MIN.	MAX.		
Noise Figure	N		6		5	dB	$V_{CE}=5\text{V}$ $I_C=200\mu\text{A}$, $R_g=2\text{K}\Omega$ $f=30\text{Hz}$ to 15KHz at -3dB points
Delay Time	t_d		35		35	ns	$V_{CC}=3\text{V}$, $I_C=10\text{mA}$, $I_{B1}=1\text{mA}$ $V_{BE(off)}=0.5\text{V}$ (See Figure1)
Rise Time	t_r		35		35	ns	
Storage Time	t_s		175		200	ns	$V_{CC}=3\text{V}$, $I_C=10\text{mA}$ $I_{B1}=I_{B2}=1\text{mA}$ (See Figure2)
Fall Time	t_f		50		50	ns	

*Measured under pulsed conditions. Pulse width=300 μs . Duty cycle $\leq 2\%$



ZETEX

Zetex plc.
Fields New Road, Chadderton, Oldham, OL9-8NP, United Kingdom.
Telephone: (44)161 622 4422 (Sales), (44)161 622 4444 (General Enquiries)
Fax: (44)161 622 4420

Zetex GmbH
Streitfeldstraße 19
D-81673 München
Germany
Telefon: (49) 89 45 49 49 0
Fax: (49) 89 45 49 49 49

Zetex Inc.
47 Mall Drive, Unit 4
Commack NY 11725
USA
Telephone: (631) 543-7100
Fax: (631) 864-7630

Zetex (Asia) Ltd.
3701-04 Metroplaza, Tower 1
Hing Fong Road,
Kwai Fong, Hong Kong
Telephone: (852) 26100 611
Fax: (852) 24250 494

These are supported by
agents and distributors in
major countries world-wide
© Zetex plc 2000

Internet: <http://www.zetex.com>

This publication is issued to provide outline information only which (unless agreed by the Company in writing) may not be used, applied or reproduced for any purpose or form part of any order or contract or be regarded as a representation relating to the products or services concerned. The Company reserves the right to alter without notice the specification, design, price or conditions of supply of any product or service.