

阅读申明

- 1.本站收集的数据手册和产品资料都来自互联网，版权归原作者所有。如读者和版权方有任何异议请及时告之，我们将妥善解决。
- 2.本站提供的中文数据手册是英文数据手册的中文翻译，其目的是协助用户阅读，该译文无法自动跟随原稿更新，同时也可能存在翻译上的不当。建议读者以英文原稿为参考以便获得更精准的信息。
- 3.本站提供的产品资料，来自厂商的技术支持或者使用者的心得体会等，其内容可能存在描述上的差异，建议读者做出适当判断。
- 4.如需与我们联系，请发邮件到marketing@iczoom.com，主题请标有“数据手册”字样。

Read Statement

1. The datasheets and other product information on the site are all from network reference or other public materials, and the copyright belongs to the original author and original published source. If readers and copyright owners have any objections, please contact us and we will deal with it in a timely manner.
2. The Chinese datasheets provided on the website is a Chinese translation of the English datasheets. Its purpose is for reader's learning exchange only and do not involve commercial purposes. The translation cannot be automatically updated with the original manuscript, and there may also be improper translations. Readers are advised to use the English manuscript as a reference for more accurate information.
3. All product information provided on the website refer to solutions from manufacturers' technical support or users the contents may have differences in description, and readers are advised to take the original article as the standard.
4. If you have any questions, please contact us at marketing@iczoom.com and mark the subject with "Datasheets" .

ATM-10N Text Display Operator Panel



The **ATM-10N** is a super bright LCD operator interface that can store up to 128 text messages and can communicate with Aromat's FP0, FPM, and FP2. A standard overlay is included or you can customize your own.



(Standard overlay)

Key Features:

- **2 System Keys**
- **4 Programmable Function Keys (Momentary, Toggle, Set, Reset)**
- **Scrolling and Flashing Messages**
- **255 Internal Recipe Storage Variables (Built-in Recipe Storage Area)**
- **Bar-Graph Data Display**
- **2 LED's for Alarm Annunciation**
- **Pass Through Communications**

SOFTWARE

ATMSOFT32 is a simple programming tool that helps you build your applications quickly and easily. Whether it is a small application to monitor data or a bigger application to monitor and change data, ATMSOFT32 can do it all. This software supports

Specifications

Display	High Brightness Backlit LCD
Display size	2 x 16 Characters
Character size	0.2 inches
LED	2
Function keys	6
Memory	64KB EPROM
Calendar Time Clock	None
Communication port	2 Ports: DSUB-15 (PLC), DSUB-9 (PC)
Password	Function Key Security Only
Expansion slot	None
Other function	None
Power Supply	5VDC (From PLC Port)
Current Consumption	180mA
Ambient temperature	32 to 122 ° F(0 to 50 °C)
Ambient Humidity	90% Non Condensing
Protection (Front)	IP65
Dimensions (mm)	108 (w) x 60 (h) x 44 (d)
Panel Cutout (mm)	90 (w) x 44 (h)
Communication Baud Rate	19,200 or 9600 BPS

Ordering Information

ATM-10N	ATM-10N
Programming Kit - includes programming cable, software, and manual	XKIT-ATM32-ALL

most of the FP Series PLCs.

System requirements include:

- 386 or higher
- Windows 3.1 or higher
- Dos Version 5.0 or higher
- Display resolution of 640 x 480 (VGA)
No EGA/CGA

Cable to PLC -
FP0/M/2 (0.5m)

AFC15205-US

Cable to PLC -
FP0/M/2 (1.5m)

AFC15215-US

Software

ATMSOFT32-CD

Program Cable

AFP15IBM-US