

## 阅读申明

- 1.本站收集的数据手册和产品资料都来自互联网，版权归原作者所有。如读者和版权方有任何异议请及时告之，我们将妥善解决。
- 2.本站提供的中文数据手册是英文数据手册的中文翻译，其目的是协助用户阅读，该译文无法自动跟随原稿更新，同时也可能存在翻译上的不当。建议读者以英文原稿为参考以便获得更精准的信息。
- 3.本站提供的产品资料，来自厂商的技术支持或者使用者的心得体会等，其内容可能存在描述上的差异，建议读者做出适当判断。
- 4.如需与我们联系，请发邮件到marketing@iczoom.com，主题请标有“数据手册”字样。

## Read Statement

1. The datasheets and other product information on the site are all from network reference or other public materials, and the copyright belongs to the original author and original published source. If readers and copyright owners have any objections, please contact us and we will deal with it in a timely manner.
2. The Chinese datasheets provided on the website is a Chinese translation of the English datasheets. Its purpose is for reader's learning exchange only and do not involve commercial purposes. The translation cannot be automatically updated with the original manuscript, and there may also be improper translations. Readers are advised to use the English manuscript as a reference for more accurate information.
3. All product information provided on the website refer to solutions from manufacturers' technical support or users the contents may have differences in description, and readers are advised to take the original article as the standard.
4. If you have any questions, please contact us at marketing@iczoom.com and mark the subject with "Datasheets" .



- "X"-Nut™ quarter wave antenna
- EM-M11001-058, NMO Cable Mount
- EMMP-058 Mini-UHF Connector

## "X"-Nut™ Antenna Kits

### Antenna Kits for Chrome Nut Antenna System Replacement

- Complete Antenna & Cable Kit, includes:
  - "X"-Nut™ quarter wave antenna<sup>1</sup>
  - NMO Cable Mount
  - Mini-UHF Connector (supplied loose)
- Stylish high-impact, dual shot Xenoy™/TPV base
- Insert molded brass NMO ring eliminates water intrusion and mating concerns of dissimilar metals
- Dual seal construction for weatherproof protection
- Durable Black Chrome finish for high conductivity and quality appearance
- Delivers up to 10% more operational bandwidth than comparable lower performance Chrome Nut designs

<i>Model</i>	<i>Frequency</i>	<i>Replaces Motorola™ Chrome Nut Kit Part No.</i>
<b>EM-MX5152-MP</b>	152-162 MHz	HAD4008A
<b>EM-MX5162-MP</b>	162-174 MHz	HAD4009A
<b>EM-MX5450-MP</b>	450-520 MHz	HAE4003A
<b>EM-MX5746-MP</b>	746-894 MHz	HAF5002A

<i>Electrical Specifications (Antenna<sup>1</sup>)</i>		<i>Mechanical Specifications (Kit<sup>1</sup>)</i>	
Impedance	50Ω	Radiator Material	300 Series SS
Gain	0 dBd, (2.0 dBi)	Radiator Plating	Black Chrome
Power Rating	100 W	Base Material	Xenoy™ w/TPV Skirt
Polarization	Linear, Vertical	Connector (supplied loose)	Mini-UHF, Plug
E-Plane	50 Degrees, Nominal	NMO Cable Mount Length	17 ft. (5.1m)
H-Plane	Omnidirectional	Operating Temperature	-40° to 85° C
Ground Plane	Required	Corrosion	Salt and UV Resistant

1. Reference specific "X"-Nut Antenna and NMO Cable Mount part numbers for detailed specifications.

All specifications subject to change without notification.

