

## 阅读申明

- 1.本站收集的数据手册和产品资料都来自互联网，版权归原作者所有。如读者和版权方有任何异议请及时告之，我们将妥善解决。
- 2.本站提供的中文数据手册是英文数据手册的中文翻译，其目的是协助用户阅读，该译文无法自动跟随原稿更新，同时也可能存在翻译上的不当。建议读者以英文原稿为参考以便获得更精准的信息。
- 3.本站提供的产品资料，来自厂商的技术支持或者使用者的心得体会等，其内容可能存在描述上的差异，建议读者做出适当判断。
- 4.如需与我们联系，请发邮件到marketing@iczoom.com，主题请标有“数据手册”字样。

## Read Statement

1. The datasheets and other product information on the site are all from network reference or other public materials, and the copyright belongs to the original author and original published source. If readers and copyright owners have any objections, please contact us and we will deal with it in a timely manner.
2. The Chinese datasheets provided on the website is a Chinese translation of the English datasheets. Its purpose is for reader's learning exchange only and do not involve commercial purposes. The translation cannot be automatically updated with the original manuscript, and there may also be improper translations. Readers are advised to use the English manuscript as a reference for more accurate information.
3. All product information provided on the website refer to solutions from manufacturers' technical support or users the contents may have differences in description, and readers are advised to take the original article as the standard.
4. If you have any questions, please contact us at marketing@iczoom.com and mark the subject with "Datasheets" .

**59020 and 59025 Firecracker Features and Benefits**



**Features**

- 2 Part Magnetically Operated Proximity Sensor
- 304mm (12") lead outs
- UL Recognised
- Choice of normally open, normally closed or change over switching
- Subminiature version also available


**Benefits**

- Quick and easy to install
- No standby power requirement
- Operates through non-ferrous materials such as wood, plastic or aluminium
- Hermetically sealed, magnetically operated contacts continue to operate long after optical and other technologies fail due to contamination

**Applications**


- Position and limit sensing
- Security
- Level sensing
- Linear actuators

**DIMENSIONS**



	<b>A Max</b>	<b>B Max</b>	<b>C ± .250 (15,24)</b>	
<b>57020</b>	(.201) 5,10	(.600) 15,24	-	
<b>57025</b>	(.245) 6,22	(1.00) 25,4	-	
<b>59020</b>	(.201) 5,10	(.650) 16,4	(12.00) 304,8	
<b>59025</b>	(.201) 6,22	(1.00) 25,4	(12.00) 304,8	File E61760(N)

**Recommended Activating Positions:**



Sensors and Matching Actuators (Note 2)		Actuator	Sensor				
Must Actuate	Must Release						
.100 (2,54)	.300 (7,62)	57020-000	59020-010	—	—	—	—
.150 (3,81)	.800 (20,32)	57025-000	—	59025-010	59025-020	59025-030	59025-040

Electrical Specifications and Operating Characteristics			Form A	Form A	Form A	Form C	Form B
Contact Type			SPST-NO Signal Level	SPST-NO Standard	SPST-NO High Voltage	SPDT-CO Standard	SPST-NC Standard
Contact Rating		Watt - max.	3	10	10	5	5
Voltage	Switching	Vdc - max.	100	200	300	175	175
	Breakdown	Vdc - min.	170	250	450	200	200
Current	Switching	A - max.	0.25	0.5	0.5	0.25	0.25
	Carry	A - max.	0.5	1.2	1.5	1.5	1.5
Resistance	Contact, Initial	- max.	0.2	0.2	0.2	0.2	0.2
	Insulation	- min.	10 <sup>10</sup>	10 <sup>10</sup>	10 <sup>10</sup>	10 <sup>10</sup>	10 <sup>10</sup>
Capacitance	Contact	p F - typ.	0.2	0.3	0.2	0.3	0.3
Temperature	Operating	°C	-40 to + 105	-40 to + 105	-20 to + 105	-40 to + 105	-40 to + 105
	Storage	°C	-65 to + 105	-65 to + 105	-65 to + 105	-65 to + 105	-65 to + 105
Time	Operate	ms - typ.	1.0	1.0	1.0	1.0	1.0
	Release	ms - typ.	1.0	1.0	1.0	1.0	1.0
Shock	11ms 1/2 sine	G - max.	100	100	100	50	50
Vibration	50-2000 Hz	G - max.	30	30	30	30	30

- Notes: 1. Flying Leads 59025 are 24 AWG 7/32 PVC, 105 deg. C., UL 1569. Leads are stripped .250 (6,35), untinned. **59020** 26 AWG, UL 1569  
 2. Order Actuators as a separate item.  
 3. Underwriters Laboratories recognition. For details on electrical specifications, contact Hamlin, Inc.

INFORMATION PROVIDED ON THIS DATA SHEET IS PROVIDED FOR INFORMATION PURPOSES ONLY AND SHOULD NOT BE RELIED UPON AS BEING ACCURATE FOR ANY PARTICULAR PURPOSE. Product performance may be affected by the application to which the product is put. Upon request, HAMLIN will assist purchasers by providing information specific to any particular application. HAMLIN disclaims any and all liability whatsoever for any purchaser's reliance upon the information contained on this data sheet without further consultation with authorised representatives of HAMLIN.

**Breed Electronics USA** Tel: 001 920 648 3000 • Fax: 001 920 648 3001 • Email: sales@hamlin.com  
**Breed Electronics UK** Tel: +44 (0) 1379 649700 • Fax: +44 (0) 1379 649702 • Email: uksales@breedtech.com  
**Breed Electronics Germany** Tel: +49 (0) 6181 953660 • Fax: +49 (0) 6181 953666 • Email: hamlin-electronics.de@breedtech.com  
**Breed Electronics France** Tel: +33 1 46 87 02 02 • Fax: +33 1 46 86 67 86 • Email: hamectrol@hamectrol.fr