

阅读申明

- 1.本站收集的数据手册和产品资料都来自互联网，版权归原作者所有。如读者和版权方有任何异议请及时告之，我们将妥善解决。
- 2.本站提供的中文数据手册是英文数据手册的中文翻译，其目的是协助用户阅读，该译文无法自动跟随原稿更新，同时也可能存在翻译上的不当。建议读者以英文原稿为参考以便获得更精准的信息。
- 3.本站提供的产品资料，来自厂商的技术支持或者使用者的心得体会等，其内容可能存在描述上的差异，建议读者做出适当判断。
- 4.如需与我们联系，请发邮件到marketing@iczoom.com，主题请标有“数据手册”字样。

Read Statement

1. The datasheets and other product information on the site are all from network reference or other public materials, and the copyright belongs to the original author and original published source. If readers and copyright owners have any objections, please contact us and we will deal with it in a timely manner.
2. The Chinese datasheets provided on the website is a Chinese translation of the English datasheets. Its purpose is for reader's learning exchange only and do not involve commercial purposes. The translation cannot be automatically updated with the original manuscript, and there may also be improper translations. Readers are advised to use the English manuscript as a reference for more accurate information.
3. All product information provided on the website refer to solutions from manufacturers' technical support or users the contents may have differences in description, and readers are advised to take the original article as the standard.
4. If you have any questions, please contact us at marketing@iczoom.com and mark the subject with "Datasheets" .



NTC Thermistors - Disc and Chip Style



Temperature Measurement and Control Thermistors

DISC and CHIP Style



**DISC & CHIP NTC
STYLE NTC THERMISTOR
Features**

-
- **Wide Ohmic Value Range**
 - **Accurate & Stable**
 - **Fast Thermal Response Time**
 - **Tight Tolerances**
 - **High Sensitivity**

NTC Thermistors

Negative Temperature Coefficient (NTC) thermistors are thermally sensitive semiconductor resistors which exhibit a decrease in resistance as absolute temperature increases. Change in the resistance of NTC thermistor can be brought about either by a change in the ambient temperature or internally by self-heating resulting from **current flowing through the device**. Most of the practical applications of NTC thermistors are based on these material characteristics.

NTC Disc and Chip Style Devices

Ametherm manufactures Disc and Chip style thermistors in **resistance values ranging from 1.0 ohm to 500,000 ohms**. These devices are suitable for a range of resistance values and temperature coefficients from relatively low resistance and temperature coefficients to very high values. Precision resistance tolerances are available to 1%. **Standard resistance tolerances are from 5% to 20%**. All tolerances are **specified at 25°C** or may be specified at any temperature within the operating temperature range of the thermistor.

Thermistor Terminology for Temperature Measurement & Control Devices

- **The dissipation constant (D.C.)** is the ratio, normally expressed in milliwatts per degree C (mw/°C), at a specified ambient temperature, of a change in power dissipated in a thermistor to the resultant change in body temperature.
- **The thermal time constant (T.C.)** is the time required for a thermistor to change 63.2% of the total difference between its initial and final body temperature when subjected to a step function change in temperature under zero-power conditions and is normally expressed in seconds (S).
- **Alpha (α) or Temperature Coefficient of Resistance** is the temperature coefficient of resistance is the ratio at a specified temperature, T, of the rate of change of zero-power resistance with temperature to the zero-power resistance of the thermistor. The temperature coefficient is commonly expressed in percent per degree C (%/°C).

$$\alpha_T = \Delta R_T / \Delta T$$

NTC DISC & CHIP

Selection

Considerations

-
- Select Req'd. Resistance Value & Temperature Coefficient

- Determine Accuracy Req'd.
- Review Power Dissipation
- Determine Operating Temperature Range
- Review Thermal Time Constant

Thermistor Applications

Time and temperature are two of the most frequently measured variables. There are numerous ways of the measuring temperature electronically, most commonly by **thermocouples and negative temperature coefficient (NTC) thermistors**. For general purpose temperature measurement, NTC temperature sensors can operate over a wide temperature range (-55 to +300°C). They are stable throughout a long lifetime, and are small and comparatively inexpensive. Typically, they have negative temperature coefficients between **-3.3 and -4.9%/°C at 25°C**. This is more than ten (10) times the sensitivity of a platinum resistance thermometer of the same nominal resistance. Ametherm's Disc & Chip style thermistors are used in many applications that require a high degree of accuracy and reliability.

Some of the most popular applications of NTC thermistors include:

- Temperature Compensation
- Temperature Measurement & Control
- Fan Motor Control
- Fluid Level & Temperature Sensors

NTC DISC & CHIP - Selection Process

- Select R Value
- Determine R @ T
- Calculate DEV for R @ T
- Evaluate Power Rating (D.C.)
- Review T.C. Requirements

Selection considerations for NTC Disc and Chip Devices

Power dissipation is a common problem in the use of thermistors as they can only dissipate a certain amount of power.

- If the **power dissipated exceeds the dissipation constant** (D.C.) rating of the sensor it is likely that it will exhibit self heating.

- Most thermistors dissipate from 1 to 25 mW/°C nominal. This means that the resistance changes by an equivalent of 1°C for each D.C. rating (mW/°C) for the selected device.
- To maintain a higher degree of accuracy, temperature error caused by self-heating should be an order of magnitude less than the required sensor accuracy. For many applications, this degree of accuracy is not required and a less stringent de-rating may be adequate.
- Several options to reduce the thermistor power are to increase the thermistor resistance, lower the source voltage and/or increase the series resistor in the divider circuit.

As an example,

- If the D.C. of the thermistor selected is **5 mW/°C** and the power dissipated by the device is 20 mW/°C, then a 4°C error is induced due to the effect of self-heating.
- To minimize this effect, a factor can be derived simply by taking the DC rating times 10-1(one order of magnitude lower) and use it in the power equation to produce a good approximation of the maximum allowable power.
- For instance, if the **desired accuracy is 1°C**, and the rated D.C. of the device selected is 5 mW/°C, adjusting the specified D.C. rating in the power equation to 0.5 mW/°C compensates for self-heating error and effectively predicts the maximum power the device can dissipate without significantly affecting the desired accuracy.
- The resulting maximum power that should be applied would be calculated as **1°C*0.5mW/°C = 0.5mW**.

NTC Standard Disc Thermistor Specifications

Part Number	Resistance @25°C (Ohms) ±10%	R-T Curve	D (in.)	THK (in.)	D.C.	T.C.	Leads AWG#	S (in)
1DA101J	100	A	0.1	0.06	3	10	28	0.07
1DA101J-EC	100	A	0.1	0.06	3	10	28	0.07
1DA101K	100	A	0.1	0.06	3	10	28	0.07

1DA101K-EC	100	A	0.1	0.06	3	10	28	0.07
1DA131J	130	A	0.1	0.06	3	10	28	0.07
1DA131K	130	A	0.1	0.06	3	10	28	0.07
1DA500J	50	A	0.1	0.03	3	6	28	0.07
1DA500K	50	A	0.1	0.03	3	6	28	0.07
1DB102J	1,000	B	0.1	0.06	3	10	28	0.07
1DB102K	1,000	B	0.1	0.06	3	10	28	0.07
1DB102K-EC	1,000	B	0.1	0.06	3	10	28	0.07
1DB501K	500	B	0.1	0.03	3	6	28	0.07
1DC103J	10,000	C	0.1	0.03	3	6	28	0.07
1DC103J-EC	10,000	C	0.1	0.08	4	12	28	0.07
1DC302J	3,000	C	0.1	0.08	4	12	28	0.07
1DC502J	5,000	C	0.1	0.08	4	12	28	0.07
1DC502J-EC	5,000	C	0.1	0.08	4	12	28	0.07
1DE104J	100,000	E	0.1	0.95	3	9	28	0.07
1DE104K	100,000	E	0.1	0.95	3	9	28	0.07
1DE104K-EC	10,000	E	0.1	0.95	3	9	28	0.07
2DA200J	20	A	0.2	0.05	7	20	24	0.1
2DA200K	20	A	0.2	0.05	7	20	24	0.1
2DA503J	50,000	A	0.2	0.05	7	20	24	0.1

2DB101K	100	B	0.2	0.025	7	18	24	0.1
2DB102J	1,000	B	0.2	0.025	7	18	24	0.1
2DB102J-EC	1,000	B	0.2	0.025	7	18	24	0.1
2DB102K	1,000	B	0.2	0.025	7	18	24	0.1
2DB151J	150	B	0.2	0.025	7	18	24	0.1
2DB151K	150	B	0.2	0.035	7	19	24	0.1
2DC102K	1,000	C	0.2	0.035	7	18	24	0.1
2DC302J	3,000	C	0.2	0.1	7	30	24	0.1
2DC302K	3,000	C	0.2	0.1	7	30	24	0.1
2DE103J	1,0000	E	0.2	0.04	7	17	24	0.1
2DE103K	1,0000	E	0.2	0.04	7	17	24	0.1
2DE503K	5,0000	E	0.2	0.04	7	17	24	0.1
3DA100J	10	A	0.3	0.06	8	48	24	0.1
3DA100K	10	A	0.3	0.06	8	48	24	0.1
3DB500J	50	B	0.3	0.025	8	35	24	0.1
3DB500K	50	B	0.3	0.025	8	35	24	0.1
3DE502J	5,000	E	0.3	0.025	8	35	24	0.1
3DE502K	5,000	E	0.3	0.025	8	35	24	0.1