

阅读申明

- 1.本站收集的数据手册和产品资料都来自互联网，版权归原作者所有。如读者和版权方有任何异议请及时告之，我们将妥善解决。
- 2.本站提供的中文数据手册是英文数据手册的中文翻译，其目的是协助用户阅读，该译文无法自动跟随原稿更新，同时也可能存在翻译上的不当。建议读者以英文原稿为参考以便获得更精准的信息。
- 3.本站提供的产品资料，来自厂商的技术支持或者使用者的心得体会等，其内容可能存在描述上的差异，建议读者做出适当判断。
- 4.如需与我们联系，请发邮件到marketing@iczoom.com，主题请标有“数据手册”字样。

Read Statement

1. The datasheets and other product information on the site are all from network reference or other public materials, and the copyright belongs to the original author and original published source. If readers and copyright owners have any objections, please contact us and we will deal with it in a timely manner.
2. The Chinese datasheets provided on the website is a Chinese translation of the English datasheets. Its purpose is for reader's learning exchange only and do not involve commercial purposes. The translation cannot be automatically updated with the original manuscript, and there may also be improper translations. Readers are advised to use the English manuscript as a reference for more accurate information.
3. All product information provided on the website refer to solutions from manufacturers' technical support or users the contents may have differences in description, and readers are advised to take the original article as the standard.
4. If you have any questions, please contact us at marketing@iczoom.com and mark the subject with "Datasheets" .

Surface Mount Multilayer Varistors

Normal Surge Protection (NA) Series

Features:

- Fast Response < 0.5 ns
- Low Capacitance
- Low Clamping Voltage and High Energy Absorption

Application Fields:

- Telecommunications
- Automotive Systems
- Data Systems
- Power Supplies

Ordering Information:

Part Number	Working Voltage (max)		Breakdown Voltage 1 mA (V)	Peak Current (max) 8/20 μ s (A)	Clamping Voltage (max)		Energy Absorption (max) 10/1000 μ s (J)	Typical Capacitance Ref. 1 KHz (pF)
	AC (V _{RMS})	DC (V)			(A)	(V)		
MLV0402NA006V0020	4	5.5	8 (7.5~10.5)	20	1	20	0.05	200
MLV0402NA009V0020	6	9	12 (10.2~13.8)	20	1	23	0.05	135
MLV0402NA011V0020	8	11	15 (12.8~17.3)	20	1	25	0.05	75
MLV0402NA014V0020	11	14	18 (15.3~20.7)	20	1	30	0.05	50
MLV0402NA018V0020	14	18	24 (21.6~26.4)	20	1	39	0.05	45
MLV0603NA006V0030	4	5.5	8 (7.5~10.5)	30	1	20	0.1	360
MLV0603NA009V0030	6	9	12 (10.2~13.8)	30	1	23	0.1	300
MLV0603NA014V0030	11	14	18 (15.3~20.7)	30	1	30	0.1	210
MLV0603NA018V0030	14	18	24 (21.6~26.4)	30	1	39	0.1	160
MLV0603NA022V0030	17	22	27 (24.3~29.7)	30	1	44	0.1	145
MLV0603NA030V0030	25	30	39 (35.1~42.9)	30	1	65	0.1	110
MLV0603NA038V0030	30	38	47 (42.3~51.7)	30	1	77	0.1	90
MLV0805NA006V0080	4	5.5	8 (7.5~10.5)	80	1	20	0.1	1400
MLV0805NA009V0080	6	9	12 (10.2~13.8)	80	1	23	0.1	650
MLV0805NA011V0100	8	11	15 (12.75~17.25)	100	1	25	0.2	410
MLV0805NA014V0100	11	14	18 (15.3~20.7)	100	1	30	0.2	350
MLV0805NA018V0100	14	18	24 (21.6~26.4)	100	1	39	0.2	300
MLV0805NA022V0100	17	22	27 (24.3~29.7)	100	1	44	0.2	250
MLV0805NA026V0100	20	26	33 (29.7~36.3)	100	1	54	0.3	220
MLV0805NA030V0100	25	30	39 (35.1~42.9)	100	1	65	0.3	200
MLV0805NA038V0100	30	38	47 (42.3~51.7)	100	1	77	0.3	150
MLV0805NA045V0080	35	45	56 (50.4~61.6)	80	1	90	0.3	110
MLV1206NA006V0100	4	5.5	8 (7.5~10.5)	100	1	20	0.2	3100
MLV1206NA014V0100	11	14	18 (15.3~20.7)	100	1	30	0.3	800
MLV1206NA018V0100	14	18	24 (21.6~26.4)	100	1	38	0.3	620
MLV1206NA022V0100	17	22	27 (24.3~29.7)	100	1	44	0.4	700
MLV1206NA026V0100	20	26	33 (29.7~36.3)	100	1	54	0.5	480
MLV1206NA030V0100	25	30	39 (35.1~42.9)	100	1	65	0.6	400

Surface Mount Multilayer Varistors

Normal Surge Protection (NA) Series

Ordering Information:

Part Number	Working Voltage (max)		Breakdown Voltage 1 mA (V)	Peak Current (max) 8/20 μ s (A)	Clamping Voltage (max)		Energy Absorption (max) 10/1000 μ s (J)	Typical Capacitance 1 KHz (pF)
	AC (V _{RMS})	DC (V)			(A)	(V)		
MLV1206NA038V0100	30	38	47 (42.3~51.7)	100	1	77	0.7	260
MLV1206NA045V0100	35	45	56 (50.4~61.6)	100	1	90	0.8	230
MLV1206NA056V0100	40	56	68 (61.2~74.8)	100	1	110	1.0	200
MLV1206NA065V0100	50	65	82 (73.8~90.2)	100	1	135	0.5	175
MLV1206NA085V0100	60	85	100 (90~110)	100	1	165	0.6	150
MLV1210NA006V0250	4.5	5.5	8 (7.5~10.5)	250	2.5	20	0.5	5200
MLV1210NA018V0250	14	18	24 (21.6~26.4)	250	2.5	38	0.8	1150
MLV1210NA022V0250	17	22	27 (24.3~29.7)	250	2.5	44	1.0	1720
MLV1210NA026V0250	20	26	33 (29.7~36.3)	250	2.5	54	1.2	610
MLV1210NA030V0250	25	30	39 (35.1~42.9)	250	2.5	65	1.4	920
MLV1210NA038V0250	30	38	47 (42.3~51.7)	250	2.5	77	1.6	780
MLV1210NA045V0250	35	45	56 (50.4~61.6)	250	2.5	90	2.0	400
MLV1210NA056V0250	40	56	68 (61.2~74.8)	250	2.5	110	2.3	300
MLV1210NA085V0200	60	85	100 (90~110)	200	2.5	165	1.4	210
MLV1812NA018V0500	14	18	24 (21.6~26.4)	500	5	38	1.7	2000
MLV1812NA030V0500	25	30	39 (35.1~42.9)	500	5	65	2.9	2500
MLV1812NA038V0500	30	38	47 (42.3~51.7)	500	5	77	3.5	2200
MLV1812NA045V0500	35	45	56 (50.4~61.6)	500	5	90	4.2	1000
MLV2220NA018V1000	14	18	24 (21.6~26.4)	1000	10	38	3.1	8500
MLV2220NA030V1000	25	30	39 (35.1~42.9)	1000	10	65	5.5	3900
MLV2220NA038V1000	30	38	47 (42.3~51.7)	1000	10	77	6.3	4600
MLV2220NA056V1000	40	56	68 (61.2~74.8)	1000	10	110	8.8	4000

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

AEM:

[MLV0603NA009V0030T](#) [MLV0805NA009V0080T](#) [MLV2220NA009V1000T](#) [MLV1210NA056V0250T](#)
[MLV1812NA085V0400T](#) [MLV1206NA009V0100T](#) [MLV1812NA090V0400T](#) [MLV0805NA014V0100T](#)
[MLV0603NA038V0030T](#) [MLV1210NA030V0250T](#) [MLV0805NA003V0040T](#) [MLV1210NA006V0250T](#)
[MLV1206NA014V0100T](#) [MLV1210NA014V0250T](#) [MLV1812NA065V0400T](#) [MLV0603NA006V0030T](#)
[MLV0805NA026V0100T](#) [MLV1812NA030V0500T](#) [MLV1206NA030V0100T](#) [MLV0603NA003V0030T](#)
[MLV1210NA017V0250T](#) [MLV2220NA017V1000T](#) [MLV2220NA026V1000T](#) [MLV1210NA038V0250T](#)
[MLV1210NA022V0250T](#) [MLV0805NA056V0080T](#) [MLV0402NA014V0020T](#) [MLV1206NA038V0100T](#)
[MLV1206NA018V0100T](#) [MLV0603NA026V0030T](#) [MLV0402NA006V0020T](#) [MLV0603NA022V0030T](#)
[MLV1206NA065V0100T](#) [MLV1206NA056V0100T](#) [MLV0805NA065V0060T](#) [MLV1812NA011V0500T](#)
[MLV1210NA065V0250T](#) [MLV2220NA038V1000T](#) [MLV2220NA011V1000T](#) [MLV1812NA017V0500T](#)
[MLV1812NA022V0500T](#) [MLV2220NA056V1000T](#) [MLV0603NA018V0030T](#) [MLV2220NA022V1000T](#)
[MLV0603NA045V0030T](#) [MLV1210NA011V0250T](#) [MLV0402NA018V0020T](#) [MLV1812NA056V0500T](#)
[MLV0805NA006V0080T](#) [MLV1206NA085V0100T](#) [MLV1812NA045V0500T](#) [MLV0402NA017V0020T](#)
[MLV0402NA003V0020T](#) [MLV0805NA045V0080T](#) [MLV1206NA017V0100T](#) [MLV1812NA038V0500T](#)
[MLV1210NA026V0250T](#) [MLV0402NA038V0020T](#) [MLV1812NA009V0500T](#) [MLV1206NA090V0100T](#)
[MLV0402NA030V0020T](#) [MLV0805NA017V0100T](#) [MLV1812NA026V0500T](#) [MLV2220NA018V1000T](#)
[MLV0402NA009V0020T](#) [MLV1812NA018V0500T](#) [MLV0805NA011V0100T](#) [MLV2220NA085V0800T](#)
[MLV2220NA090V0800T](#) [MLV0402NA026V0020T](#) [MLV2220NA014V1000T](#) [MLV0805NA030V0100T](#)
[MLV0805NA018V0100T](#) [MLV0805NA022V0100T](#) [MLV0603NA011V0030T](#) [MLV1206NA003V0060T](#)
[MLV2220NA065V0800T](#) [MLV1812NA014V0500T](#) [MLV1210NA085V0200T](#) [MLV1206NA022V0100T](#)
[MLV1206NA026V0100T](#) [MLV1210NA045V0250T](#) [MLV0402NA011V0020T](#) [MLV1210NA009V0250T](#)
[MLV0603NA030V0030T](#) [MLV1206NA006V0100T](#) [MLV0805NA038V0100T](#) [MLV2220NA045V1000T](#)
[MLV0603NA017V0030T](#) [MLV1210NA018V0250T](#) [MLV1812NA127V0300T](#) [MLV2220NA030V1000T](#)
[MLV0402NA022V0020T](#) [MLV1206NA011V0100T](#) [MLV1210NA090V0200T](#) [MLV0603NA014V0030T](#)
[MLV1206NA045V0100T](#) [MLV0402NA014V0020TM](#) [MLV0402NA018V0020TM](#) [MLV0402NA011V0020](#)